

# CX1200e CX1000e FX1200e

## Welche Mediengröße kann der CX1200e und FX1200 verarbeiten?

<b>CX1200</b>		
	<b>Min</b>	<b>Max</b>
Etiketten Höhe	None	17 " (431.8 mm)*
Etikettenbreit mit Position	None	7.5" (190.5 mm)
Etiketten Breite	None	8" (203.2 mm)
Medien Breite	8.5" (216 mm)**	8.5" (216 mm)**
Medien Dicke	5 mils (total)	12 mils (total)***
Außendurchmesser	N/A	12" (305 mm)
Rollen-Kern	N/A	3" (76.2 mm)
Roll Gewicht	N/A	45 lbs (20.4 kg)

<b>FX1200</b>		
	<b>Min</b>	<b>Max</b>
Etiketten Höhe	.75" (19 mm)	24" (609 mm)*
Etiketten Breite	.75" (19mm)	8" (203 mm) no target
Medien Breite	4.5" (114 mm)	8.5" (216 mm)
Rollen Außendurchmesser	N/A	12" (305 mm)
Rollen-Kern	N/A	3" (76.2 mm)
Rollen Gewicht	N/A	45 lbs (20.4 kg)

\* Die Werte sind die empfohlenen Werte. Ändeurngen auf eigenen Wunsch

\*\* You must use 8.5" (216mm) media. Using narrower will cause damage to your fuser and cause toner NOT to adhere to the media.

\*\*\* Thicker media can be fed into the printer if you attach a 3 ft leader of thinner mat

If you want to buy the [CX1200](#) or the [FX1200](#), please click the links which leads you to our shop.

Eindeutige ID: #1201

Verfasser: n/a

Letzte Änderung: 2014-07-08 15:48